

## **BASIC STEPS TO RESET THE Strong SRT Silver Receiver to receive the new TV Plus frequency**

Please note that these settings are ONLY if you have a single antenna directed to the current TV PLUS satellite service. These steps are NOT compatible if you have two antennas connected to the TV PLUS receiver either by a DISQ or 22k Switch. If you have two antennas contact your satellite installer for further instructions.

### **Basic New Channel Scan Process**

1. Press Menu on Remote
2. The MAIN MENU will show & the Installation Bar will be highlighted Blue arrow left
3. Enter Pin '0000' Dish Setting on the right side will be highlighted orange
4. Press 'DOWM' arrow on the remote until the orange bar is highlighting 'Manual Scan' & press OK
5. The Manual Scan menu will show, press the Green Button on the remote to 'Add TP'
6. Frequency Bar will be highlighted press 12557 & press 'DOWM' arrow on the remote
7. Symbol Rate bar will be highlighted press 13845 & press 'DOWM' arrow on the remote
8. Polarization will show press < button on remote so 'H' shows
9. Once you have entered these parameters the Level & Quality bar should be between 45% – 65%
10. Press the OK on the remote to start the scan
11. Scan Result Screen will appear with TV & RADIO LIST Boxes on the screen saying 14 TV Channels
12. RTS Sat should show

You now have your channels.

If for some reason this is unsuccessful do the following factory reset and then repeat the above steps

Once you had done the search 14 new channel names should appear

BUT because you DO NOT have the new TV PLUS receiver you will only be able to watch

RTS / BN / PINK PLUS/ PINK EXTRA

You will hear the audio on channels

A2 / MELOS / RTRS / ATLAS / DM SAT/ KOPNIKUS / B92 / DUGA / SOS/ A1

If you wish to purchase a receiver to watch the above channels contact TV PLUS